

University of Mumbai

Examinations Summer 2022

Time: 2 hour 30 minutes

Max. Marks: 80

Q1.	Choose the correct option for following questions. All the Questions are compulsory and carry equal marks
1.	Which of the following applies to periodic continuous time signals:
Option A:	$x(n) = x(N + n)$
Option B:	$x(t) = e^{st}$
Option C:	$x(t) = x(t + T_0)$
Option D:	$X(Z) = (z - 1) X(z)$
2.	The energy of the signal, $x(n) = u(n)$ is:
Option A:	1 J
Option B:	$\frac{1}{2} J$
Option C:	∞J
Option D:	0 J
3	If $x_1(n) = \{1, 2, 3\}$ and $x_2(n) = \{1, 1, 1\}$, then what is the convolution sequence of the given two signals?
Option A:	{1, 2, 3, 1, 1}
Option B:	{1, 2, 3, 4, 5}
Option C:	{1, 3, 5, 6, 2}
Option D:	{1, 3, 6, 5, 3}
4.	If $L\{x(t)\} = X(s)$ then $L\{x(at)\}$ will be
Option A:	$ a X\left(\frac{s}{a}\right)$
Option B:	$\frac{1}{ a } X\left(\frac{s}{a}\right)$
Option C:	$ a X\left(\frac{a}{s}\right)$
Option D:	$\frac{1}{ a } X\left(\frac{a}{s}\right)$
5.	Two Cascade connected discrete time systems with impulse responses $h_1(n)$ and $h_2(n)$ can be replaced by a single equivalent discrete time system with impulse response,
Option A:	$h_1(n) * h_2(n)$
Option B:	$h_1(n) + h_2(n)$
Option C:	$h_1(n) - h_2(n)$
Option D:	$h_1(n)$
6.	Laplace Transform of the signal $x(t) = u(t-1)$
Option A:	$1/s - 1$
Option B:	e^{-s}/s
Option C:	$e^{-s}/(s-1)$
Option D:	$(s-1)$

7.	If $Z\{x(n)\} = X(z)$ then
Option A:	$Z\{x(-n)\} = -X(z)$
Option B:	$Z\{x(-n)\} = X(-z)$
Option C:	$Z\{x(-n)\} = -X(z^{-1})$
Option D:	$Z\{x(-n)\} = X(z^{-1})$
8.	$y(t) = x(t/2)$ represents a
Option A:	compressed signal
Option B:	expanded signal
Option C:	time-shifted signal
Option D:	amplitude scaled signal by the factor of 2
9	Fourier Transform of DT unit impulse signal is
Option A:	-1
Option B:	1
Option C:	0
Option D:	Undefined
10	For a stable system which of the following is correct?
Option A:	$ z < 1$
Option B:	$ z = 1$
Option C:	$ z > 1$
Option D:	$ z \neq 1$

Q2. (20 Marks)	Solve any Four out of Six (5 marks each)
A	Function $x(t)$ is shown in figure. Draw even and odd parts of $x(t)$
B	Determine following signal is periodic or not. If periodic, determine the fundamental period $10 \sin(12\pi t) + 4 \sin(18\pi t)$
C	Determine Laplace transform and ROC of signal $x(t) = e^{2t} u(t) - e^{4t} u(-t) + 6 t^3 - 3 \sin 5t$
D	Prove the shifting property of Z transform
E	Determine whether the system described by $y(t) = x(0.5t)$ i) Linear ii) Time invariant
F	Perform convolution using graphical method $x(t) = t u(t) \quad h(t) = e^{-t} \text{ for } t \geq 0$

Q3 (20 Marks)	Solve any Two Questions out of Three (10 marks each)
A	<p>For a CT signal $x(t) = 8 \cos (200\pi t)$ Find</p> <ol style="list-style-type: none"> 1. Nyquist rate 2. If $f_s = 120$ Hz , write the equation for DT signal $x(n)$ 3. If $f_s = 250$ Hz, write the equation for DT signal. <p>Comment on result obtained in 2 & 3.</p>
B	<p>A continuous time LTI system is represented by differential equation</p> $\frac{d^2y(t)}{dt^2} + 3\frac{dy(t)}{dt} + 2y(t) = x(t)$ <ol style="list-style-type: none"> i)Determine transfer function ii)Obtain step response iii)Obtain impulse response
C	<p>Obtain inverse Laplace transform of</p> $x(s) = \frac{3s+7}{(s+1)(s-3)}$ <p>for ROC $R_{e(s)} > 3$, $R_{e(s)} < -1$ & $-1 < R_{e(s)} < 3$</p>

Q4. (20 Marks)	Solve any Two Questions out of Three (10 marks each)	
A	Solve any Two	5 marks each
i.	Obtain Discrete time Fourier transform and magnitude plot of $h(n) = \{0, 1, 1, 1\}$	
ii.	Determine the spectra of periodic signal (Discrete time Fourier series) $X(n) = \{1, 1, 1, 0\}$ with period $N=4$	
iii.	Obtain the continuous time Fourier transform of 1)Unit step and 2)Unit impulse	
B	Solve any One	10 marks each
i.	Find impulse response for all possible ROC conditions for a transfer function given by $x(Z) = \frac{Z(Z^2 - 4Z + 5)}{(Z-1)(Z-2)(Z-3)}$	
ii.	Obtain continuous time Fourier series of saw tooth wave shown in figure	