

[3 Hours]

[Total Marks : 80]

Please check whether you have got the right question paper.

CBCGS

Biomedical

- N.B:
1. Q. 1 is Compulsory.
 2. Attempt any three questions from Q.2 to Q.6
 3. Assume suitable data wherever required.

1. (A) Find $X(z)$ if $x(n) = \cos(\omega_0 n)u(n)$ (05)
 (B) Find IDFT if $X[k] = \{2, 1+j, 0, 1-j\}$ (05)
 (C) Compare FIR and IIR filters (05)
 (D) Convert analog filter to digital filter by Impulse Invariant Technique. Transfer function is given by $H(s) = \frac{1}{(s+4)(s+2)}$. Assume $T = 1$ sec (05)

2. (A) Obtain Direct form I, Direct form II, Cascade realization of given Transfer function, (10)

$$H(z) = \frac{1 + \frac{1}{4}z^{-1}}{\left(1 + \frac{1}{2}z^{-1}\right)\left(1 + \frac{1}{2}z^{-1} + \frac{1}{4}z^{-2}\right)}$$

- (B) Prove convolution property of DFT, using the same find output response if, $x(n) = \{1, 2, 3, 4\}$ and $h(n) = \{1, 2, 2, 1\}$

3. (A) Find $x(n)$ if $H(z) = \frac{1}{1 - \frac{1}{4}z^{-1} - \frac{1}{8}z^{-2}}$ for all possible ROCS. (05)

- (B) Find DTFT: $x(n) = 2^{-n}u(n)$ (05)

- (C) Using unilateral Z transform, determine zero input, zero state and total response of (10)
 system described by difference equation: $y(n) = \frac{1}{2}y(n-1) + x(n)$

Input is $\left(\frac{1}{3}\right)^n u(n)$. Initial condition: $y(-1) = 1$

4. (A) A linear phase FIR filter has desired frequency response: (10)

$$H_d(e^{j\omega}) = 0 \quad \text{For } \frac{-\pi}{4} \leq \omega \leq \frac{\pi}{2}$$

$$= e^{-j2\omega} \quad \text{For } \frac{\pi}{4} < \omega \leq \pi$$

Design filter using Hamming Window.

- (B) Derive 8 point, Radix 2, DITFFT Algorithm and draw flow graph where (10)
 $x(n) = \{1, 2, 3, 4, 4, 3, 2, 1\}$

5. (A) Explain overlap and Add, overlap and save methods of linear filtering using an example (10)
- (B) Design digital Butterworth filter having following specifications: (10)
- Attenuation in pass band: 3 dB
 - Attenuation in stop band: 15 dB
 - Passband frequency: 0.5π rad
 - Stopband frequency: 0.75π rad
 - Using BLT method of mapping.
6. (A) For given specifications, find order and cut off frequency of chebyshev filter: (06)
- $0.9 \leq |H(e^{j\omega})| \leq 1$; ω : from 0 to 0.2π
 - $|H(e^{j\omega})| \leq 0.1$; ω : from 0.5π to π
- Using BLT.
- (B) Explain how many Additions and Multiplications are required to compute 'N' point DFT and using 'N' point FFT Algorithm. (06)
- (C) Explain Any two applications of DSP in the field of Biomedical. (08)