

Duration 3 Hours

[Maximum Marks 80]

NOTE:-1) Question 1 is compulsory. Solve any four out of five questions.**2) Solve any three from the remaining five questions****3) Assume suitable data if necessary.****4) Figures to the right indicate full marks**

- Q1 a. Find the IDFT of $Y(K) = \{1, 0, 1, 0\}$ 5
- b. Find the linear phase realization of FIR filter defined as 5
- $$H(Z) = \frac{1}{4} + \frac{1}{2}Z^{-1} + \frac{3}{4}Z^{-2} + \frac{1}{2}Z^{-3} + \frac{1}{4}Z^{-4}$$
- c. Compare the computational complexity of FFT algorithm and DFT for $N=4$ 5
- d. What is pre-warping in BLT? 5
- e. Explain the concept of group delay and how it can affect the output of a filter. 5
- O2, a. Compute the circular convolution of $x(n) = \{2, 1, 2, 1\}$ and $h(n) = \{1, 2, 3, 4\}$ by using FFT-IFFT method. 10
- b. Design an FIR lowpass filter using rectangular window with passband gain of 0 dB, cutoff frequency of 200 Hz, sampling frequency of 1 kHz. Assume the length of the impulse response as 7. 10
- O3 a. Find DFT of sequence $x(n) = n + 1$ for $0 \leq n \leq 7$ using DIF-FFT algorithm 10
- b. Design an analog Butterworth filter that has a -2dB passband attenuation at a frequency of 20rad/sec and atleast -10dB stopband attenuation at 30rad/sec 10
- O4 a. Determine $H(z)$ that results when the bilinear transformation is applied to analog filter defined by equation 10

$$H(s) = \frac{s^2 + 4.525}{s^2 + 0.692s + 0.504}$$

Assume $T=1$ sec.

- b Find the effect of coefficient quantization on pole locations of the given second order IIR system, when it is realized in direct form I. Assume a word length of 4 bits through truncation including a sign bit. 10

$$H(z) = \frac{1}{1 - 0.9z^{-1} + 0.2z^{-2}}$$

- O5 a. i) Given a second-order transfer function $H(Z)$. Find Cascade form realization. 10

$$H(z) = \frac{1 + \frac{3}{4}z^{-1} + \frac{1}{8}z^{-2}}{1 - \frac{5}{8}z^{-1} + \frac{1}{16}z^{-2}}$$

- ii) Given a second-order transfer function $H(Z)$. Find parallel form realization.

$$H(z) = \frac{(1 + z^{-1})(1 + 2z^{-1})}{(1 + \frac{1}{2}z^{-1})(1 - \frac{1}{4}z^{-1})(1 + \frac{1}{8}z^{-1})}$$

- b A FIR filter is given by, $y(n) = x(n) + \frac{2}{5}x(n-1) + \frac{3}{4}x(n-2) + \frac{1}{3}x(n-3)$ 10
Draw the Lattice structure.

- Q6 a. Explain application of DSP in echo cancellation. 10
b. Explain the concept of overflow limit cycle oscillations 10