

B.E (comp) B.Tech
 Sem VII CBGS
 Image Processing
 (3Hours)

QP Code : 5994

[80 Marks]

- N.B. : 1) Question No.1 is compulsory
 2) Attempt any Three questions out of remaining.
 3) Assume suitable data wherever necessary and state them clearly.

1. Answer the following:- (20)
 - (a) What do you understand by zero memory operation.
 - (b) Discuss different discontinuities in image.
 - (c) What is an Unitary matrix .
 - (d) Define Morphological operations Erosion and Dilation
2. (a) Discuss color models for a digital image.
- (b) For the given 3 bits per pixel, 4×4 size image perform following operations (10)
 - (i) Intensity level slicing with background, $r_1 = 3$ and $r_2 = 5$
 - (ii) Bit plane slicing.

6	2	3	2
1	5	0	7
4	3	2	1
2	5	7	6
3. (a) Explain: The first difference makes the chain code invariant to rotation. (10)
 (b) Explain Homomorphic filtering with the help of block diagram. (10)
4. (a) Write 8×8 Hadamard transform matrix and its signal flow graph for fast Hadamard transform. Using this butterfly diagram (Signal flow graph) compute Hadamard transform for $x(n) = \{1, 2, 1, 1, 3, 2, 1, 2\}$ (10)

 (b) Find the DCT of the given Image using matrix multiplication method. (10)

$$f(x, y) = \begin{bmatrix} 2 & 4 & 4 & 2 \\ 4 & 6 & 8 & 3 \\ 2 & 8 & 10 & 4 \\ 3 & 8 & 2 & 1 \end{bmatrix}$$
5. (a) Discuss the different types of redundancies in images with examples. (10)
 (b) Construct Improved Gray Scale (IGS) quantization code for given gray scale data, (10) {100, 110, 124, 124, 130, 200, 210}. Also Compute e_{rms} (root mean square error).
6. Write detail notes on (any Two) (20)
 - (a) Edge Linking using Hough transform
 - (b) Thinning with example.
 - (c) Differential Pulse Code Modulation (DPCM)
 - (d) Segmentation techniques: Region growing and split and merge.